



FEATURES



OHV

Over Head Valve easy to maintenance



OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.



MAINTENANCE FREE BATTERY

It is long life



WHEEL KIT

Compact case design with pulling handle for easy moving



ONE PUSH START

Autostart with single button push



GENERATOR SET OUTPUT SOCKETS

2 Receptacle AC Sockets



REMOTE START

Wireless remote start



LED DISPLAY

LED screen to monitor voltage and current with hourmeter

GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	3.5
Maximum Power (kW)	3.8
AC Rated Current (A)	15.2
AC Voltage (V)	230
DC Rated Current	12V 8A
Frequency (Hz)	50
Number of Phase	1
Power Factor	1
Fuel Consumption 100% (lt/h)	2
Fuel Consumption 75% (lt/h)	1,5
Fuel Consumption 50% (lt/h)	1
Fuel Tank Run-time (hours)	12 (50% Load)
Noise Level (dB(A) @7m.)	71.3 (50% Load)
Number of Poles	9
Receptacle Sockets	2x12V 8A
Battery Recharger	12 Vdc - 6.5 Ah



ENGINE SPECIFICATIONS

Engine Speed (rpm)	3600
Engine Output (kWm)	6.4
Bore and Stroke	70x58
Compression Ratio	8,6
Number of Cylinders	1
Displacement (cc.)	224
Fuel Type	Gasoline
Oil Capacity (ml.)	600
Fuel Tank Capacity (L)	12
Starter Type	Automatic / Remote / Recoil
Cooling System	Air Cooled

DIMENSIONS AND WEIGHT

Width (mm.)	540
Length (mm.)	745
Height (mm.)	610
Weight (kg)	47.5